

# E4000 115V 50HZ HUK

### **ENERGY AT FAIR PRICE**



Simple professional generator. Pramac has designed this generator to ensure a high performance level at attractive price. Powerful and strong generator; easy to maintain, it will be soon essential to all your activities.

Main Features		
Frequency	Hz	50
Voltage	V	115
Power factor	cos ф	0.9
Phase and connection		1

Power Rating		
Standby power LTP	kVA	3.4
Standby power LTP	kW	3.1
Continuous power COP	kVA	2.9
Continuous power COP	kW	2.6

Ratings definition (According to standard ISO8528 1:2005)
COP - Continuous Power: It is defined as being the maximum power which a generating set is capable of delivering continuously for an unlimited number of hours, with the maintenance intervals and procedures

being carried out as prescribed by the manufacturers.

LTP - Limited-Time running Power: It is defined as the maximum power available, under the agreed operating conditions, for which the generating set is capable of delivering for up to 500 h of operation per year (whose no more than 300 for continuative use) with the maintenance intervals and procedures being carried out to a practical with the maintenance intervals and procedures being carried out as prescribed by the manufacturers. No overload capability is available.

Engine specifications		
Engine manufacturer		Honda
Model		GX200
Engine cooling system		Air
Displacement	cm³	196
Aspiration		Natural
Operating Speed-Nominal	rpm	3000
Speed governor		Mechanical
Fuel		Petrol
Oil capacity	I	0.6
Starting system		Recoil



Alternator Specifications		
Туре		
Class		Н
IP protection		23
Poles		2
Frequency	Hz	50
Voltage regulation system		Capacitor

Dimensional data		
Length	(L) mm	625
Width	(W) mm	455
Height	(H) mm	455
Dry weight	Kg	36
Fuel tank capacity	1	3.1

Autonomy		
Fuel consumption @ 75% PRP	l/h	1.17
Fuel consumption @ 100% PRP	l/h	1.57
Running time @ 75% PRP	h	2.65
Running time @ 100% PRP	h	1.97

Noise level		
Guaranteed noise level (LWA)	dB(A)	96
Noise pressure level @ 7 mt	dB(A)	68

# www.pramac.com

## **GENSET CONTROL**

### COMMANDS

Selector switch: OFF - ONStarting systems: Recoil

- Fuel Cock

### **PROTECTIONS STANDARD**

- Thermal protection

- Oil Guard

### **SOCKET TYPE**

2P+T CEE 115V 16A IP44

4



